

## Four side trim function and fully automatic double-sided lamination.

Join the **Revo Revolution** with the all new **Revo Flex** fully automatic laminator.

The **Revo Flex** 4 side trimming system allows for true flush cuts or encapsulating a sheet with lamination. The position of the cuts are fully adjustable to create perfect flush cuts or custom size encapsulation borders. No need for additional processing to trim all 4 sides of a sheet. Feeding, laminating, cutting and trimming are now fully automated with the press of the start button.

## The next generation laminating system.

### New Various Run Modes

to reduce or eliminate trimming waste. 70% less trim waste than other systems even when running in full trim mode. No waste mode totally eliminates between the sheet trim when encapsulating sheets.

### Reliable Feeding System

with adjustable resist roller pressure to stop multi-sheet feeds over a range of paper stocks from 16lb bond to 130lb cover weight.

### Adjustable Speed

from 27.5 -78.8 inches per minute allowing you to create perfect dwell time for your particular sheet weight and film thickness.

### Easy to Use Touch Panel

puts all user adjustments at your fingertips like setting trim margins, adjusting speed, setting temperature, and other controls.



Sheet Feed Skew Adjustment



With/No Margin Adjustment



FOUR  
FOUR  
FOUR  
FOUR  
FOUR  
FOUR  
FOUR  
FOUR  
FOUR  
FOUR

<b>Max. Laminating Width</b>	12.6 inches
<b>Max. Laminating Thickness</b>	0.4 mm including paper and film
<b>Laminating Film Thickness</b>	1.5, 3, 5 mil
<b>Laminating Film Type</b>	Gloss, Matte
<b>Laminating Speed</b>	0.7 - 2.0m (= 27.5 - 78.7 inch)/min
<b>Temperature</b>	Variable, digital LCD: 176-284°F
<b>Warm-up Time</b>	5 minutes
<b>Power</b>	120V or 240V
<b>External Dimensions</b>	51" x 24" x 42.5" (with stand, feeder tray, extension tray, stacker)
<b>Weight</b>	154 lbs.
<b>Feeder Tray Capacity</b>	200 sheets (80 lb. bond)

COMMON SHEET SIZES	
<b>Letter</b>	11" x 8.5"
<b>Double Letter</b>	11" x 17"
<b>Digital 1</b>	12" x 18"
<b>Digital 2</b>	13" x 19"
<b>Min. Sheet: W x L</b>	7.75" x 6.75"
<b>Max. Sheet: W x L</b>	13" x infinite (long mode)

ACCESSORIES
Feeder Tray, Extension Tray, Stacker, Power Cable, Instruction Manual, Trash Can, Stand, Stand Assembly Manual, Tools (for stand assembly), Screws (for stand assembly)

**fuseFX**

89 Moody Road, Enfield, CT 06082  
Tel: 563-271-8096 • www.fusefxcorp.com